## TOA CEILING MOUNT SPEAKER 5INCH 6W PC-1860S

## **■**DESCRIPTION

The PC—1860S Ceiling Mount Speaker features an mounting bracket for safety installation. The PC—1860S is suitable for announcement and music use in high quality sound cone speaker. Speaker design that harmonize with venue's architecture and decor.

## ■ SPECIFICATIONS

Rated Input	6 W (100 V line), 3 W (70 V line)
Rated Impedance	100 V line: 1.7 kΩ (6 W), 3.3 kΩ (3 W), 6.7 kΩ (1.5 W), 13 kΩ (0.8 W)
·	70 V line: 1.7 kΩ (3 W), 3.3 kΩ (1.5 W), 6.7 kΩ (0.8 W), 13 kΩ (0.4 W)
Sensitivity	94 dB (1 W, 1 m) (500 Hz - 5 kHz, pink noise)
Frequency Response	80 Hz - 20 kHz (peak -20 dB)
Speaker Component	12 cm (5") cone-type
Dispersion (1 to 4k Hz avg.)	165° Horizontal 175° Vertical
Dimensions for Fixing Hole	
	Ceiling thickness: 5 - 25 mm (0.2" - 0.98")
Speaker Mounting Method	Spring catch
Operating Temperature	-10 °C to +50 °C (14 °F to 122 °F)
Applicable Cable	Solid wire: 0.5 - 3 mm² (AWG 20 - 12)
Connection	Push wire connection (Bridging terminal—2 branch type)
Finish	Frame: Steel plate, white (RAL 9016 equivalent), paint
	Grille: Steel net, white (RAL 9016 equivalent), paint
	Mounting bracket: Steel plate, plating
Dimensions	Ø180 X 5 (exposed section) + 101 (D) mm (7.09" X 0.2" + 3.98")
Weight	750 q (1.65 lb)
Accessory	Paper pattern …1

## \*Use BB-1864 Back Can

