

**JUST ADD SPEAKERS.** The POWERNODE EDGE combines streaming sources, control and amplification in one sleek and affordable player. All you need to do is connect a pair of passive speakers to experience an incredible all-in-one HiFi solution. Control all your music with the intuitive BluOS Controller app. Play from a personal music library, or even directly from an external USB drive. Easily connect wired sources, like a TV or turntable, with HDMI eARC or the combo analog/digital input. Add the PULSE SUB+ wireless subwoofer for a powerful but compact 2.1 stereo system or even use the POWERNODE EDGE to power the rear channels of a wireless Bluesound surround sound setup.

PACKED WITH POWER. Bring your speakers to life with the powerful, punchy 2 x 40 watts DirectDigital™ amplifier in the POWERNODE EDGE, handling hi-res, 24 bit/192 kHz files and MQA-encoded tracks with ease. Enjoy clarity in playback of everything from densely-layered heavy metal tracks to whisper-quiet dialogue in movies and TV shows.

INTUITIVE CONTROL. Control is always at your fingertips via the BluOS Controller app for iOS, Android, Mac, or PC, or using the elegant capacitive touch panel for quick-access controls like Play, Pause, and Volume Up/Down. The POWERNODE EDGE is connected to your home network via Wi-Fi or Ethernet, integrating seamlessly with the most popular smart home control systems like Crestron, Control4, URC, RTI, ELAN, and others. Hands-free control is possible with voice assistants like Siri, Alexa, and Google Voice.

**SLEEK AND VERSATILE.** The POWERNODE EDGE is designed with a compact form factor to suit any décor and comes with a multi-orientation wall mounting bracket to hide in closets or behind sofas. Easy to spec and simple to stack, smart home installers will appreciate its 1U rack height and half-rack width, along with an easy-access touch control panel for everyday playback functions and configuration.

DIRECTDIGITAL™ AMPLIFIER PLATFORM
40 WATTS PER CHANNEL INTO 8 OHMS

QUAD-CORE 1.8GHz ARM® CORTEX™ A53 PROCESSOR

HDMI eARC, OPTICAL & ANALOG AUDIO INPUTS

BluOS™ WIRELESS MULTI-ROOM MUSIC CAPABILITY

APP CONTROL WITH ADJUSTABLE AUDIO SETTINGS

MQA MUSIC AND HI-RES AUDIO STREAMING

**AIRPLAY 2 INTEGRATION** 

WORKS WITH AMAZON ALEXA AND GOOGLE ASSISTANT

DUAL-BAND WI-FI + GIGABIT ETHERNET

TWO-WAY aptX™ HD BLUETOOTH

WIRELESS HEADPHONE OUTPUT

WIRED & WIRELESS SUBWOOFER OUTPUT

IR REMOTE LEARNING CAPABILITY

FRONT PANEL TOUCH CONTROLS

**COMPACT 1U FORM FACTOR** 

EASY FOUR-WAY MOUNTING SYSTEM

**BLACK OR WHITE FINISH** 



# POWERNODE EDGE Specifications

#### **AUDIO**

Supported Audio File Formats: MP3, AAC, WMA, WMA-L, OGG, ALAC, OPUS Supported Hi-Res Audio File Formats: FLAC, MQA, WAV, AIFF, MPEG-4 SLS

Supported Multi-Channel Audio Formats: Dolby® Digital Native Sampling Rates: up to 192 kHz

Rit Denth: 16-24

Audio Controls & EQ: BluOS Controller App

Signal-to-Noise Ratio: -91dBA

Distortion: THD+N, 0.008%

Amplification: DirectDigital™

Rated Power Output: 40W x 2 (8 Ohms)

IHF Dynamic Power: 80W (4 Ohms) / 50W (8 Ohms)

Minimum Impedance: 4 Ohms

#### **SOFTWARE & INTEGRATIONS**

Operating System: BluOS

App Controller Operating System: iOS, Android, Windows, macOS

Processor: ARM® Cortex™ -A53, Quad-Core, 1.8GHz per core

Supported Network File Sharing:Server Message Block (SMB) up to 200,000 filesAlbum Art Supported:JPG, PNG

Music Services & Internet Radio:23+3rd-Party Integrations:AirPlay 2Spotify Connect<br/>Tidal Connect

Control System Integrations: Crestron, Control 4, RTI, ELAN, URC, Lutron Voice Control Integrations: Amazon Alexa Skills; Actions on Google

BluOS Home Theater: Yes - rear surround channels

#### CONNECTIONS

 Power Supply:
 Universal bi-pin AC cord input (100-240AC)

 Ethernet/LAN:
 Ethernet RJ45, Gigabit 1000 Mbps

 Wi-Fi Built In:
 Wi-Fi 5 (802.11ac), dual-band

 Bluetooth Quality:
 Bluetooth 5.0 aptX HD

 Bluetooth Connectivity:
 Two-Way (transmit & receive)

IR Optical Built In: IR Sensor Built In - front panel with IR Remote Learning

IR Input: 3.5mm Jack

Optical/Analog Input: Combo - Mini TOSLINK/Stereo 3.5mm

HDMI Input: HDMI eARC

**USB IN:** Type A (Fat32 Formatted)

**Headphone Output:** Bluetooth only

Subwoofer Output: RCA x 1; Wireless to PULSE SUB+

**Speaker Terminals:** 5-Way Binding Post

## **USER INTERFACE & CONTROL**

 Status Indicator:
 LED

 Play/Pause Button:
 Touch LED

 Volume Control Buttons:
 Touch LED

 Previous/Next Track Buttons:
 Touch LED

 Preset Buttons:
 In-App only

## **GENERAL**

Storage Environment: -10°C to 50°C, 20% to 80% relative humidity

Operating Environment: 0°C to 40°C

Finish: Black/White; Matte Satin Paint

Version: N230

All specifications subject to change without notice.



Front View



Rear View



## **Product Dimensions**

 $219 \times 44.5 \times 193$  mm (W x H x D) 8.6 x 1.75 x 7.6 in (W x H x D)\* **Weight:** 1.37kg/3.02lbs

### **Included Accessories**

- 120V AC Power Cord
- 230V AC Power Cord
- Ethernet Cable
- TOSLINK Optical to 3.5mm Mini Adapter
- Metal Mounting Bracket
- Metal Mounting Screw
- Rubber Mount Attachment
- Safety/Warranty Guide
- Quick Setup Guide
- \* Non-metric measurements are approximate.

